



BA102 ADDRESSABLE MANUEL CALL POINT

BA102 Addressable Resettable Call Point is designed for manual notification of fire or emergency situation in the addressable fire system. It can be activated by pressing the resettable glass in front of it. There is an animated notification led and when the button is active, this led stays on constantly. After pressing the glass, it can be reset with special key. When the button is pressed and activated, it transmits the fire information to the control panel over the communication line. The address given to the MCP by the RB1201 Address Programmer is saved and stored in the memory.



TECHNICAL SPECIFICATIONS

Loop Operating Voltage	:16 to 30 VDC
Loop Operating Current	:<600 μ A @ 24 VDC (average with led blink)
Maximum Alarm Current	:<7 mA @ 24 VDC (included led blink)

ENVIRONMENTAL SPECIFICATIONS

Humidity	:10% to 93% (Relative Humidity, Non-condensing)
Operating Temperature	: -10°C to 50°C

MECHANICAL SPECIFICATIONS

Width	:90 mm
Height	:90 mm
Depth	:27 mm
Weight	:160 Gram

GENERAL FEATURES

- Durable and aesthetic ABS plastic case
- Programmable address information in permanent memory
- Programmable with RB1201 Address programmer
- Led indicator
- Resettable with special key
- EN54-11 certified

